arXiv:1409.4514v1 [physics.acc-ph] 16 Sep 2014

Low emittance lattice for the storage ring of Turkish Light Source Facility TURKAY*

Z. Nergiz[1;1)] A. Aksoy[2;2)]

[1] Nigde University, Department of Physics, Faculty of Letter and Science, 51200 Nigde, Turkey
[2] Institute of Accelerator Technology, Ankara University, Ankara 06100, Turkey

Abstract: TAC (Turkish Accelerator Center) project is aimed to build an accelerator center in Turkey. The first step of the project is to construct IR-FEL facility. The second stage is to build a synchrotron radiation facility named TURKAY, which is the third generation synchrotron radiation light source that aimed to achieve high brilliance photon beam from low emittance electron beam at 3 GeV. The electron beam parameters highly depend on the magnetic lattice of the storage ring. In this paper a low emittance storage ring for TURKAY is proposed and beam dynamic properties of the magnetic lattice are investigated.

Key words: TURKAY, storage ring, beam dynamics, synchrotron radiation

PACS: 29.20.-c, 29.20.dk, 41.60.Ap

1 Introduction

Turkish Accelerator Center (TAC) project has been proposed to build an accelerator center in Turkey in order to use accelerators and accelerator based light sources for research & development (R&D) in Turkey and its region [1]. The first step of TAC, which is under construction since 2010, is building an InfraRed Free Electron Lasers (IR-FEL) facility covering the range of 3-250 microns [2]. The second stage is proposed to be a Synchrotron Radiation (SR) facility named TURKAY, which is the third generation light source that aimed to achieve high brilliance photon beam from low emittance electron beam [3, 4]. The project is now entering its detailed design phase: after the completion of the conceptual design report.

The third generation light sources can be classified as low energy, intermediate energy (2-4 GeV) and high energy light sources. The disadvantage of low energy sources is that high quality x-ray beam can not be produced. In contrast to cost of low energy sources the high energy sources are quite expensive. Thermal loading in the beam line equipment is also another problem of high energy light sources. In the last decades the intermediate and high brightness light sources have become more preferred light sources. Photon energy ranged from few ev to 100 keV can be produced by the development of the insertion devices technology. Therefore, the intermediate energy light sources require relatively lower construction budget and can provide relatively wide photon energy range. According to this comparisons and the requirements of synchrotron radiation users from the light source user meetings arranged by TAC project, the main goals of TURKAY are determined. Therefore, it has been decided to reach very low emittance value at 3 GeV electron beam energy and relatively short storage ring circumference. The emittance value of the storage ring should be below 1 nm rad.

2 Optical structure of storage ring

One of the important parameters of a light source is the brilliance which is defined as the number of photons emitted per second, per photon energy bandwidth, per solid angle and per unit source size. The brilliance can be expressed as [5, 6]

$$B = \frac{dN/dt}{4\pi^2\sigma_x\sigma_{x'}\sigma_y\sigma_{y'}\frac{\Delta\omega}{\omega}} \approx \frac{flux}{4\pi^2 K\varepsilon_x^2} \qquad (1)$$

where K is the coupling constant and ε_x is the natural emittance. The flux depends on the beam current, undulator period and undulator deflection parameter. So, the brilliance of a storage ring is strongly related to the natural emittance and in order to maximize it, the horizontal and vertical emittances must be as small as possible.

Emittance is defined as the area of the phase ellipse

Received 14 March 2009

∗ Supported byTurkish Republic Ministry of Development with Grant No:DPT2006K120470.

1) E-mail: znergiz@nigde.edu.tr

2) E-mail: aaksoy@ankara.edu.tr

©2013 Chinese Physical Society and the Institute of High Energy Physics of the Chinese Academy of Sciences and the Institute of Modern Physics of the Chinese Academy of Sciences and IOP Publishing Ltd

and it is characteristic of a storage ring. The emittance is correlated to the beam cross section via

$$\sigma_{x,y} = \sqrt{\varepsilon_{x,y}\beta_{x,y}} \tag{2}$$

where $\beta_{x,y}$ is one of the Twiss parameters which is a position dependent quantity and it describes the beam focusing at that point.

In a storage ring, the optical structure is basic part of the machine and the main parameters of the stored beam is determined by the magnetic lattice. The main consideration of the magnetic lattice is to achieve low emittance electron beam in order to obtain high brilliance photon beam.

The zero current natural emittance in an electron storage ring governed by

$$\varepsilon_0 \sim \frac{E^2}{N_s^3 N_d^3} \tag{3}$$

where E is the electron beam energy, N_s is the number of sector and N_d is the number of the bending magnets [7]. According to this equation, it is decided to work on multi bend lattice.

Four bending magnet lattice structure is designed for main cell to get low emittance beam. The main cell consists of 4 bending magnets and 4 different type (16) quadrupole magnets. Figure 1 shows the betatron and dispersion functions of main cell.



Fig. 1. Betatron and dispersion functions in main cell for finite dispersion mode.

The ring has finite dispersion in straight sections and its emittance value is 0.51 nm rad. The lattice optics can be easily tuned to achromatic lattice by adjusting the strength of the quadrupoles. In achromatic case the emittance is 0.93 nm rad.

The storage ring is composed of 20 main cells and its circumference is 477 m. The working point is chosen where the resonance driving terms and tune shifts are as small as possible. 7 families of sextupoles are used to correct chromaticity and to compensate nonlinearities. In total, there are 80 bending magnets, 320 quadrupoles and 460 sextupoles in the whole ring. The length of straight sections is considered to be 5 m for rf cavity, insertion devices and injection requirements. Number of the straight sections is 20; two of them for injection and rf cavity and the rest sections are for undulators. Main consideration on the number of bending magnets and sections comes from the limitation of the circumference and budget. The bending magnets are 1.5 m long and the magnetic field in the bending magnets is 0.52 T. The advantage of the low field of the bending magnets is low rf power requirement.

The main parameters of storage ring are listed in Table 1 for finite dispersion and achromatic modes. OPA [8], MADX [9] and BEAMOPTICS [10] codes are used to design magnetic lattice of storage ring.

Table 1. The main parameters of storage ring.

Parameters	F. D. Mode	Achr. Mode
Energy (GeV)	3.0	3.0
Circumference (m)	477	477
Beam Current (mA)	500	500
H. Emittance (nm rad)	0.51	0.93
V. Emittance (nm rad)	0.0051	0.0090
Energy Loss/part./turn (keV)	375.1	375.1
Max.β_x (m)	12.7	15.4
Max. β_y (m)	25.3	28.1
β_x in the mid. of str. sec. (m)	12.7	15.4
β_y in the mid. of str. sec. (m)	7.5	9.8
D_x in the mid. of str. sec. (m)	0.09	0.00
Betatron Tunes Q_x/Q_y	31.19/6.15	36.24/6.18
Natural Chromaticity ξ_x/ξ_y	-70/-38	-84/-43
Corrected Chromaticity ξ_x/ξ_y	0.0/0.0	0.0/0.0
Number of straight sections	20	20
Length of straight section (m)	5	5
RMS Energy Spread (%)	0.05	0.058
Damping Time H/V/L (ms)	26.9/26.9 /13.4	25.5/25.5/12.7
RF Voltage (MV)	3.5	3.5
RF Frequency (MHz)	500	500
Harmonic Number	795	795
Bunch Charge (nC)	1	1
RMS bunch length (mm)	2.1	2.1
Momentum Acceptance (%)	4.8	5.6
Mom. Compaction Factor	0.00032	0.00025
Coupling (%)	1	1
Touschek Lifetime (h)	10.5	18.6
Radiation Integrals		
I1 (m)	0.135068624	0.1234583687
I2 (m^{-1})	0.328986813	0.3289868134
I3 (m^{-2})	0.017225709	0.0172257092
I4 (m^{-1})	0.000370301	0.00033846813
I5 (m^{-1})	0.000023149	0.0000248347

In a low emittance lattice, strong focusing leads to high

chromaticity. Therefore, it is needed to use strong sextupoles to correct the natural chromaticity that limits the dynamic aperture. Two sextupoles are used for chromaticity corrections and those sextupoles leads to tune shift. They should be placed in suitable places to minimize the nonlinear effects. One of them ($k_2 > 0$) is located to the beginning of the lattice where β_x is large and β_y is small. The second one ($k_2 < 0$) is located where the point β_y is large and β_x is small. The purpose of the other 5 sextupoles are to compensate the nonlinear effects of the chromatic sextupoles. Their locations and strengths are determined by the use of OPA simulation code and the goals are to keep the dynamical aperture as possible as large and to keep the particles away from the resonance lines.

3 Nonlinear beam dynamic

The dynamic aperture is the stable transverse area for the particle in which it can execute its oscillations safely without getting defused or lost. Storage rings require a large dynamic aperture in order to achieve good injection efficiency and good beam lifetime. Large dynamic aperture is also an indication of high beam stability. ELEGANT code [11] is used to determine dynamical aperture. The dynamical aperture for different momentum offset and for several magnet error situations are demonstrated in Figs. 2 and 3, respectively. It can be seen from the figures that the dynamical aperture is large enough for such a low emittance ring and effects of the magnet error is not high.



Fig. 2. Dynamical aperture of storage ring for different momentum offsets (1024 turn, magnet errors is zero).



Fig. 3. Dynamical aperture of storage ring for different magnet errors (1024 turn, momentum offset is zero).

Frequency Map Analysis (FMA) [12] is a numerical method, which is a way to understand the effect of resonance to the dynamic aperture. For this purpose diffusion rate

$$D = Log_{10}\sqrt{\Delta\nu_x^2 + \Delta\nu_y^2} \tag{4}$$

can be used as stability index [13]. $\Delta\nu_x$ and $\Delta\nu_y$ are transverse tune shifts of surviving particles in tracking. Figure 4 shows the dynamical aperture from FMA results of single particle tracking without synchrotron radiation.



Fig. 4. The effects of the resonance to dynamical aperture from Frequency Map Analyses.

One of the important nonlinear issue of a low emittance storage ring is intrabeam scattering which is the coulomb scattering within a beam that usually increase the beam emittance. The horizontal beam emittance and relative energy spread with intrabeam scattering are [14, 15]

$$\varepsilon_x = \frac{T_x}{T_x - \tau_x}\varepsilon_{x0}, \tag{5}$$

$$\sigma_\delta = \frac{T_x}{T_x - \tau_p}\sigma_{\delta 0} \tag{6}$$

where T_x and T_p are the horizontal and longitudinal intrabeam scattering growth rates, τ_x and τ_p are the horizontal and longitudinal radiation damping times and ε_{x0} and $\sigma_{\delta 0}$ are the zero current horizontal emittance and relative energy spread.

The emittance value with intrabeam scattering is calculated by using ELEGANT code. The obtained emittance value is 0.70 nmrad for 500 mA average beam current, 3.5 MV rf voltage and 500 MHz rf frequency. This emittance value is used at brilliance and flux density calculations mentioned in next section.

Another nonlinear beam dynamics effect is Touschek lifetime. It is the limitation due to Touschek scattering which describes a collision of two electrons inside a bunch with transfer of transverse momentum into longitudinal momentum. According to the simulation results on the storage ring the Touschek lifetime is 10.5 h. It is planned to operate the machine in top-up operation mode of that aims to maintain a steady current in a storage ring by periodically injecting small amounts of current.

4 Radiation properties

The radiation spectrum is investigated by the example of some existing or planned insertion devices from other synchrotron radiation facilities [16] with some little changes. The amended undulator parameters are sown in Table 2.

Table 2. The main parameters of insertion devices.

Parameters	CU18	SU15	IU28	U90
Period Length (cm)	1.8	1.5	2.8	9
Number of Period	222	67	142	44
Min. Gap (mm)	5	5.6	7	35
K_{ymax}	2.25	2.10	2.35	10
Length (m)	4.0	1.005	4.0	4.0
Photon Energy (keV)	1.4-20	1.8-23	0.8-12	0.1-3

IU28 is in vacuum undulator with 28 mm period length. The CU18 cryogenic permanent magnet undulator can provide brilliance value up to 1.7×10^{21} photon $s^{-1}mrad^{-2}per0.1\%BW$. SU15 the superconducting undulator with period length of 15 mm can provide photons in energy range 1.4-20 keV. U90 is conventional permanent magnet undulator with period length 9 cm. The brilliance is calculated with SPECTRA code [17] and obtained graphic is presented in Fig. 5.



Fig. 5. Brilliance spectrum.

5 Conclusion

The storage ring for TURKAY is designed and its storage ring parameters are presented. 0.51 nm rad emittance value is achived with relatively short circumference. The nonlinear effects are also investigated. It is seen that dynamical aperture values are large enough for such a low emittance ring. The brilliance value more than 10^{21} $photon/s/\%0.1BW/mm^2/mrad^2$ can be provided by this storage ring parameters with appropriate undulators.

6 Acknowledgment

The authors would like to thanks to H. Wiedemann. This work was supported by Turkish Republic Ministry of Development with Grant No:DPT2006K120470.

References

1 www.thm.ankara.edu.tr.
2 A. Aksoy, Ö. Karslı, Ö. Yavaş, "The Turkish Accelerator Complex IR FEL Project", Infrared Physics & Technology, v:51, p:378-381, (2008)
3 A. Aksoy et. al., Turkish Accelerator Center: The Status and Road Map IPAC14, 2921, 2014.
4 Z. Nergiz, H. Aksakal, A. Aksoy, C. Kaya, O. Kurtulus Ozturk, The Status of Turkish Synchrotron Radiation Source Machine Design, IPAC14, 313, 2014.
5 K. Wille and J. Mcfaal," The Physics of Particle Accelerators", Oxford University Press, (2001) p. 193.
6 D. Bilderback, P, Elleaume and E. Weckert,J. Phys. B: At. Mol. Opt. Phys., 38 (2005) p. 773.
7 M. Borland, ANL/APS/LS-337, 2013.
8 Andreas Streun, OPA version 3.39 PSI, March 14, (2012).
9 H. Grote and F. Schmidt, "The MAD-X Program", http://mad.web.cern.ch.
10 H.Wiedemann, BEAMOPTICS, Applied Physics Department, Stanford University.
11 M.Borland, "Elegant:A Flexible SDDS-Compliant Code for Accelerator Simulation", Technical Report, Advanced Photon Source, 2000.

12 J. Laskar, "Introduction to the Frequency Map Analysis", edited by C.Simo, NATO Adv. Study Inst., Kluwer Academy Pub. (Dordrecht, The Netherlands, 1999).
13 L. Nadolski, J. Laskar, Phys. Rev. ST Accelerators and beams, 6, 114801 (2003).
14 K.L.F. Bane, A Simplified Model of Intrabeam Scattering, Proceedings of EPAC Paris, 2002.
15 A. Wolski, "Intrabeam scattering in the NLC main damping ring",LBNL-59525,CBP Tech Note-319, 2004.
16 C. S. Hwang, "Planning of the insertion devices for the 3 GeV Taiwan Photon Source", Proceedings of PAC07, New Mexico, USA (2007), p. 1082.
17 T. Tanaka and H. Kitamura, "SPECTRA: a synchrotron radiation calculation code", J. Synchrotron. Radiat. 8 (2001) 1221.